

PX3 SideKX Panel Installation

TOOLS REQUIRED: #1 Phillips Screwdriver, plastic coated pliers, or small spanner wrench, and a 10mm Socket or nut-driver DO NOT USE an ADJUSTABLE WRENCH or an OPEN END WRENCH,

Loosen the 4 knurled knobs at the bottom corner of each end panel. Start on the right end (no connectors or silk screened logos), using the #1 Phillips screwdriver remove and SAVE both Phillips screws (4-40 3/16"). Then remove the factory end panel and replace it with the SideKX panel, reinstall using the two screws you just removed.

Now for the left end panel (having the connectors and silk screened logos), REMOVE the NUT and washer from the DC power connector using the 10mm Socket to twist it loose. Next remove the knurled nuts on both ACC1 jacks You can remove the nuts with a small screwdriver or other tool pressed gently in the slot, or use plastic tipped pliers, taking care NOT to scratch the paint. Again, remove and SAVE the two Phillips Screws (4-403/16") using a #1 Philips screwdriver, then remove the factory end panel.

To install the new SideKX panel use the following technique. First place the panel over the ACC1 PC and the ACC1 XCVR jacks, pushing the jacks into the holes. Then screw the knurled nuts on to the 3.5mm jacks. These knurled nuts must be installed first to ensure the nuts fit properly into the recessed openings and contact the spot faced bare metal on the end panel. Note the knurled nuts have slots on the side facing away from the panel. You can tighten these nuts with a small screwdriver or other tool pressed gently in the slot, or use plastic tipped pliers, taking care NOT to scratch the paint. Now you can attach the washer and 10mm nut back onto the DC power connector and snug it down with the socket. Then reinstall the two Phillips screws you removed and tighten down the knurled knobs on all four corners.

The SideKX Cover will now snap in, going between the handles and seating in the holes.

Thanks for purchasing your SideKX Panels **73 Scott AK6Q**

Patent Pending

GEMS [Products.com](http://GEMSProducts.com)